

### Weltlader „Glob“



Worldwide Use  
EU/USA/AUS/UK Plug



2x USB-A Ports



Resettable 10A Fuse



Input: 100-250V AC  
Output: 10A Max.

Produkt Info



Egal wo Sie sind können Sie mit dem Weltlader Glob sicher sein dass Ihre Geräte sicher betrieben oder geladen werden können. Dank der **variabel einstellbaren Stecker** ist der Adapter mit **EU, USA, AUS und UK** Steckdosen kompatibel. Einfach einen der drei Schieberegler in die Position der gewünschten Steckdosen-Version einstellen und dann einstecken. Mit einem EU Stecker und **2 USB Anschlüssen** können Sie ein Haushaltsgerät benutzen und haben immer noch genug Ladekapazität für zwei Smartphones oder ähnliche Geräte. Der Glob ist Perfekte Begleiter für ihren nächsten **Urlaub** oder Ihre **Geschäftsreisen** ins Ausland.

Der Adapter ist mit einer **10A Sicherung** ausgestattet um ihre Geräte gegen Überladungen oder Kurzschlüsse zu schützen.

#### Technische Daten:

- Eingangsspannung: 100V-240V AC
- Eingangsfrequenz: 50/60Hz
- Ausgangsstrom: 10A (1000W/100V oder 2500W/250V)
- Gesamtleistung: 12 Watt
- Durchschnittliche Effizienz im Betrieb: 81,3%
- Effizienz bei geringer Last (10 %): 78,55%
- Leistungsaufnahme bei Nulllast: 78,55% Watt
- 2 USB-A Anschlüsse 5V DC/2.4A
- Eingebaute rückstellbare 10A Sicherung

No matter where you are, thanks to the World Charger Glob you can always be sure that your devices can be used or charged safely.

Thanks to the **variably adjustable plug** the adapter is compatible with **EU, USA, AUS and UK** sockets.

Simply adjust one of the three slide controls on the side to the desired plug and plug the adapter in. With one EU Plug and **2 USB outputs** you can use an appliance whilst loading 2 devices.

It's the perfect companion for your next **holiday** or **business trip** abroad.

The adapter is equipped with a **10A fuse** to ensure your devices are protected from overloads or short circuits.

#### Technical Data:

- Input Voltage: 100V-240V AC
- Input Frequency: 50/60Hz
- Output Current: 10A (1000W/100V or 2500W/250V)
- Total Power: 12 Watts
- Average active efficiency: 81,3%
- Efficiency at low load (10%): 78,55%
- No-load power consumption: 78,55% Watts
- 2 USB-A outputs 5V DC/2.4A
- Built-in resettable 10A fuse

Art.Nr: 253737

EAN: 4024559253737

Technische Änderungen vorbehalten / Improvement and changes of the technical specifications and other data's could be made without prior notice